

POLMAR DB-50M

Radio in MODE 1 Menu

(In MODE 1 the Menu is different from the default MODE 2)

(Page = Page in Polmar DB-50M Manual § = Section * = menu number not available in Polmar manual)

No.	Definition	Default	My set	Discription	Page	§
1	APO	Off		Automatic Power Off – timer setting	19	2
2	ARS	Off		Automatic offset – TX Freq. +/- offset Freq.	19	3
3	Step	2.5		Frequency Channel Step setup in Hz	19	4
4	BAND	On		Band On or Off – VFO scanning in the current band	20	1
5	BEEP	On	Off	Beep On or Off	20	2
6	CLKSFT	Off		CPU Clock freq. Change – CPU Clock interfere Freq.	20	3
7	2TN ENC	00		2 Tone Encode select	*	
8	5TN ENC	00		5 Tone Encode select	*	
9	DTMF ID	Off		Radio's DTMF self ID enquiry	*	
10	5TON ID	Off		5 Tone self IG enquiry	*	
11	SCR	Off		Scrambler setup	*	
12	X–RPT	X-Start		Cross Band Repeat	*	
13	TON DEC	Off		Add optional signaling	*	
14	TX CDCS	Off		CTCSS Encode setup	21	1
15	RX CDCS	Off		CTCSS Decode setup	22	1
16	DSP SUB	Freq.		Sub Band Display setup	22	2
17	DTMF D	500ms		DTMF encode pre-loading time	22	3
18	DTMF S	50ms		DTMF encode transmitting time	23	1
19	DTMF W	-----		DTMF Encode setup	23	2
20	SGN SQL	SQ		Squelch mode setup	23	3
21	COMP	Off		Compander	24	1
22	TBST	1750Hz		Tone burst (Repeater)	24	2
23	KEYMOD	Key 1		Keypad (Upper/Lower) mode setup	25	1
24	LOCK	Off		Keypad Lockout	26	1
25	LOCKT	Off		TX Off (PTT Lockout)	26	2
26	SQL	04	02	Squelch level	26	3
27	REV	Off		Frequency (Repeater) Reverse	26	4
28	MUTE	TX		Sub Band Mute setup	27	1
29	NAME C	-----		Editing Channel name	27	2
30	HYPER	Auto		Channel function Auto Storage setup	27	3
31	PG PA	VFO/MR		Programmable Microphone Keys PA	28	1
32	PG PB	Talk	REV	Programmable Microphone Keys PB	28	1
33	PG PC	Scan		Programmable Microphone Keys PC	28	1
34	PG PD	Off	W/N	Programmable Microphone Keys PD	28	1
35	RF SQL	Off		RF Squelch Level setup	28	2
36	RPT MOD	Off		Offset direction (Repeater – or +) setup	28	3
37	SCAN	Time	Busy	Scan Dwell Time setup	28	4
38	SCAN M	Mem		Priority channel scan	29	1
39	SHIFT	600	0.000	Offset frequency setup (Shift Repeater)	29	2
40	DISPLAY	Freq	Name	Display Mode setup	29	3
41	REPLOCK	Off		Busy channel lockout	30	1
42	TOT	2 Min	3 Min	Time out timer on TX	30	2
43	VFOTR	Off		VFO frequency linkage	31	1
44	WIDNAR	Narrow	Wide	Wide or Narrow band	31	2
45	COL RED	1	10	LCD backlight Red setup	31	3
46	COL GRN	32	10	LCD backlight Green setup	31	3
47	COL BLU	32	25	LCD backlight Blue setup	31	3
48	DIMMER	32	16	Microphone keypad backlight brightness level	32	1
49	NOTE	--		Calling record of the last 16 call	32	2
50	AM	On	Off	AM function	32	3
51	AUT AM	Auto	Off	Automatic AM function	32	4
52	VSPCONT	Int		VHF External speaker port	33	1
53	BP–VOL	Low		Beep volume control	33	2
54	TALK	Off		Talk around	33	3
55	HND SPK	MSPK Off		microphone speaker	33	4
56	PASSWD	Off		Enter Password	34	1